# 6 Head Hi-Fi Stereo Video Recorder

# HiFiStereo

- Turbo Drive
- Smart Picture
- ShowView / VideoPlus +
- Automatic Longplay Recording
- NTSC Playback
- Turbo Timer
- Follow TV
- Front A/V Connectors

Silver Shadow





| PHILIPS                        | NICAM HIFI STEREO<br>Smart Picture - Turbo Timer - Follow TV | VR.150 Volus Reserver          |
|--------------------------------|--|--------------------------------|
| TURBO<br>DRIVE WES HO SHOWVIEW |  | RECORD STOREARCE HER R.M. TRO. |





## 6 Head Hi-Fi Stereo Video Recorder



### **Product** information

## **Reception - Installation**

- Tuner: Hyperband, UHF, VHF
- Tuning Presets: PLL, CH entry, 99 presets
- Tuning Install Features: Auto Search, Auto Install
- TV Related Functions: 16:9 (pin 8), Direct Record, Follow TV Time/Date Download: PDC (Time/Date), Text (Time)

#### **User Interface**

- Record Speed: Long Play, Standard Play
- Record Speed Selection: Auto LP, Per Menu
- · Picture Improvement System: Digital Studio Picture Control, Smart Picture
- · Audio Recording Level: Automatic
- Special Features: Auto Standby, Channel Name Display

#### **On Tape Standard**

· Additional Playback Standard: NTSC Playback on PALTV

#### **Remote Control Unit**

- Remote Control Type Number: RT306/111
- Remote Control Codes: VCR1, TV Commands

#### **Connectors Rear**

- EXT1: Black, Euro CVBS in/out
- EXT2: Black, Euro CVBS in, Euro Decoder
- Rear Audio Connector: Cinch stereo out
- Terrestrial Antenna In/Out: 75 Ohms (IEC type)

#### **Connectors Front**

• Front A/V Connectors: Cinch CVBS in, Cinch Stereo in

#### Tape Deck

- Number of Video / FM Audio / Flying Erase Heads: 4 / 2 / 0
- Play: +1
- Still Features: Perfect
- · Index Related Functions: Next/Prev. index search
- · Head Cleaning: Automatic
- Tape Length Recognition: Automatic
- Tape Counter: Linear Relative (h.m.s), Tape Position Indicator, Time Left (h.m)
- Winding / Rewinding Time (E180): 70 sec.

#### Programming

- Number of Events: 8/year
- Special Timer Programming: Turbo Timer
- Record Link: SCART 2

#### General

- Voltage: 198 264 V
- Frequency: 50Hz
- Standby Power Cons.: <3 W
- Backup Presets: 1yr
- Backup Clock Calendar Timer Event: 1mn
- Set Size W x D x H in mm: 435 x 226 x 92
- Packaging W x D x H in mm: 501 x 307 x 180
- Equipement Supplied: Aerial Cable, Batteries for RC

|  | VR750/58   | VR750/39                          | VR750/16  | VR750/07                 | VR750/02  |
|--|--|-----------------------------------|---|--------------------------|---|
| TV Systems Off Air                             | PAL B/G, PAL D/K,<br>SECAM B/G, SECAM D/K              | PAL B/G, SECAM B/G,<br>SECAM L/L' | PAL B/G   | PAL I                    | PAL B/G   |
| Sound Systems                                  | German Stereo, Mono,<br>NICAM                          | German Stereo, Mono,<br>NICAM     | German Stereo, Mono,<br>NICAM                                   | Mono, NICAM              | German Stereo, Mono   |
| OSD Menu Languages                             | Czech, English, Hungarian,<br>Polish, Russian Cyrillic | Dutch, French, German             | Dutch, English, French,<br>German, Italian,<br>Spanish, Swedish | English                  | Dutch, English, French,<br>German, Italian,<br>Spanish, Swedish |
| Record / Playback Standard                     | MESECAM, PAL   | MESECAM, PAL, SECAM               | PAL   | PAL                      | PAL   |
| Record Control &<br>Transmitter Identification | PDC, VPS   | PDC, VPS                          | PDC, VPS  | PDC                      | PDC, VPS  |
| Programming System                             | Showyiew Manual Timer                                  | Showyiew Manual Timer             | Showyiew Manual Timer   | VideoPlus + Manual Timer | Showyiew Manual Timer   |

**Product Highlights** 

quality to your personal taste.

• New Turbo Drive deck

Speed

Reliability

Intelligence

the screen.

• Turbo Timer

• 1 minute accuracy

• Minimum of steps

down to the VCR.

• Record Link

details on a high quality recording.

The new Turbo Drive deck offers:

70-second ultra fast rewind speed.

a cassette is inserted or ejected.

• No need to switch the TV "on"

• All necessary information visible on the VCR display

gets deactivated again, the recording will also stop.

Smart Picture puts you in control and gives you the chance to adjust the picture

You can adapt the picture rendition to the quality of tape used or the tape content

itself. You can, for instance, filter out the noise of a poor rental tape or increase the

To guarantee an optimum reliability, the heads are automatically cleaned each time

The Tape Position Indicator, in wind and re-wind situations, displays the accurate

"Turbo Timer" is a real time-saver for programming a timer for the next 24 hours:

• All steps are carried out using the remote control avoiding the need for bending

"Record link" is the answer if you want to record a programme from your satellite

via the Scart cable connection and will start recording simultaneously. If the receiver

To prepare for a recording only the timer of the satellite receiver needs to be programmed. The VCR will automatically detect the activation of the satellite receiver

receiver or any other external device when you are not at home.

a moving/blinking arrow. At any time, you can follow the tape movement on

position of the tape on the screen and indicates progress by means of

SMART Picture

er | 2

#### Subject to modification without notice

ShowView and Video+ are registered Trademarks of Gemstar Development Cooperation.

www.philips.com pww.videq.ce.philips.com

